

RF DETECTOR

RF detector is a portable device that helps you protect your privacy. Although these devices have been mostly used by the police, the army and government departments, anyone can use them to detect bugs or hidden cameras. This goes a long way into protecting your privacy.

Specification:

Frequency Range: 1MHz-8000MHz

detecting the dynamic range: <73Db detection sensitivity: ≤0.03mw (main frequency)

Detect range:

2.4GHz wireless camera: 15m² (standard 10mW camera)

1.2GHz wireless camera: 10 m² (standard 10mWcamera)

Can detect High-speed upload GPS locator packet locator

Can detect hidden 5.8GHZ wireless camera

Mobile: 2G, 3G, 4G: 10 m²

Indicating: 9level LED Luminous instructions/modulation sound instructions

Power: built-in 3.7 V 800mAH lithium polymer battery

Working current: 70mA

working time: 12 hours

Standby Time: 20 days



RF DETECTOR

دستگاه RF Detector ساخته شده آشکار کننده سیگنالهای رادیویی در بازه فرکانسی 1MHz الی 8GHz بوده و قابلیت آشکار کردن انواع فرستنده RF (صوت-تصویر-دیتا) را در بازه کاری خود دارد. از قابلیت‌های مهم RF Detector آشکار کردن تجهیزات جاسوسی مخفی (دوربین, میکروفن...) می باشد که ارتباط آنها به صورت رادیویی بوده. محدوده وسیع عملکرد دستگاه به مصرف کننده امکان شناسایی، ردیابی و تعیین موقعیت میکروفن های مخفی، بیسیم، تجهیزات شنود، دوربینهای مخفی بیسیم، امواج تلفن همراه و غیره را می دهد.

مشخصات فنی :

فرکانس کاری	محدوده اندازه گیری	نوع آشکارسازی	توان مصرفی	آمپر
1MHz ~ 8GHz	-60 dBm~3dBm	تصویری + صوتی	450 MW	80 mA

